

10-12-00

CERTIFICATE OF MAILING BY "EXPRESS MAIL" A

"EXPRESS MAIL" MAILING LABEL NUMBER

EL547919302US

DATE OF DEPOSIT

10/10/2000

I HEREBY CERTIFY THAT THIS PAPER OR FILE IS BEING DEPOSITED WITH THE UNITED STATES PATENT SERVICE "EXPRESS MAIL POST OFFICE TO ADDRESSEE" SERVICE UNDER 37 CFR 1.51 ON THE DATE INDICATED ABOVE AND IS ACKNOWLEDGED BY THE COMMISSIONER OF PATENTS AND TRADEMARKS, WASHINGTON, D.C. 20001

ERIC LINK

(TYPED OR PRINTED NAME OF PERSON MAILING PAPER OR FEE)

(SIGNATURE OF PERSON MAILING PAPER OR FEE)

Case No. 00AU11952023

ASSISTANT COMMISSIONER FOR PATENTS
WASHINGTON, DC 20231

Transmitted herewith for filing is the patent application of:

Inventors: Serge FRUHAUF
Alain Christophe POMET
Robert LEYDIER

For: MULTI-MODE SMART CARD, SYSTEM AND ASSOCIATED METHOD

Enclosed are:

- ☒ Patent Application: 44 pages, 33 Claims
☒ 26 sheets of drawings.
☒ An assignment of the invention to STMicroelectronics, Inc.
☒ A declaration and power of attorney.
☒ A Citation Under 37 CFR 1.97 and PTO-1449.

JC914 U.S. PTO
09/686327
10/11/00

The filing fee has been calculated according to the Patent Application filed herewith as shown below:

FOR:	(Col. 1)		(Col. 2)		SMALL ENTITY		LARGE ENTITY	
	# FILED		# EXTRA		RATE	FEE	RATE	FEE
BASIC FEE						\$ 380	OR	\$ 710
TOTAL CLAIMS	33	-20	13		X 9	\$	OR X 18	\$ 234
INDEP CLAIMS	4	-3	1		X 39	\$	OR X 78	\$ 78
[] MULTIPLE DEPENDENT CLAIM PRESENTED					+	\$	OR	
* If the difference in Col. 1 is less than "0", enter "0" in Col. 2.					TOTAL	\$ ***	TOTAL	\$ 1,022

- ☒ Enclosed is a check in the amount of \$ 1,022.00 to cover:
☒ Filing Fee

- ☒ Enclosed is a check in the amount of \$ 40.00 to cover:
☒ Recording Assignment

- ☒ The Commissioner is authorized to charge or credit any discrepancies in fee amounts to Deposit Account No. 01-0484.

PLEASE DIRECT ALL CORRESPONDENCE TO:

LISA K. JORGENSEN, ESQUIRE
STMicroelectronics, Inc.
1310 Electronics Drive
Carrollton, Texas 75006-5039

October 10, 2000
Date

PAUL J. DITMYER
Reg. No. 40,455
(407) 841-2330

Allen, Dyer, Doppelt, Milbrath & Gilchrist, P.A.
Attorneys-At-Law, 255 S. Orange Avenue, Suite 1401, P.O. Box 3791, Orlando, Florida 32802-3791

MULTI-MODE SMART CARD, SYSTEM AND ASSOCIATED METHODS

Field of the Invention

The present invention relates to information processing and storage, and more particularly, to smart card systems.

Background of the Invention

Smart cards (SC) are plastic cards having an embedded Integrated Circuit (IC). That IC may be a logic circuit with its associated memories or a microcontroller with its associated memories and software, or a microcontroller with its associated memories and software coupled to a custom block.

To use the computing power given by the IC, a SC makes use of a full set of packaging technologies. The die size varies from 1mm^2 to 30 mm^2 . The die size is limited for mechanical aspects going with the plastic nature of the SC. The IC is attached to a lead frame and wire-bonding techniques are used to connect the IC pads to the lead frame contacts. Potting and other strengthening methods protect the IC against chemical and mechanical stresses. Contacts are located on one side of the card and their number is limited to eight. Ultimately SC

performs transactions with a SC reader using a serial
protocol. All the mechanical and electrical
specifications of SC are published by the
International Standard Organization (ISO). The
5 ISO7816-X standards have allowed the simple and
massively produced magnetic stripe cards to evolve
toward the SC. SC, depending of the IC complexity,
may perform pre-paid accounting, cryptographic
scheme, personal authentication using PIN code or
10 biometrics and run java scripts to name few.

ISO documents ISO 7816-1 Physical
Characteristics, ISO 7816-2 Dimensions and Locations
of the contacts, ISO 7816-3 Electronic signals and
transmission protocols and, ISO 7816-10 Electronic
15 signals and answer to reset for synchronous cards are
incorporated herein by reference.

Today all the SC readers have to be recognized
by the infrastructure prior to perform any
transaction involving a SC. The infrastructure is
20 running an application in which the SC is involved.
The SC reader expects a SC. The half duplex protocol
between the SC and the SC reader, in which, either
the SC sends information to the SC reader or vice
versa, cannot start until a SC is detected in place
25 into the SC reader. The infrastructure manages
authentication or transactions for pre-paid cards in
public telephony, for Bank cards in Point Of Sale
(POS) terminals and Automatic Teller Machines (ATM),
for Pay TV providers in set top boxes and for
30 wireless telecom operators in Subscriber
Identification Modules (SIM) in Global System for
Mobile (GSM) terminals. Except for SIM cards, all
others applications use a physical sensor to detect
the SC. This sensor tells the SC reader when a SC is
35 in place that is when the SC lead frame contacts are

able to mate with the SC reader contacts. Two sorts
of SC reader contacts can be used, contacts that
remain in place and because of their elasticity can
slide over the SC when inserted in the SC reader or
5 mobile contacts which descend to touch the lead frame
contacts once the card has been detected in place.
When the SC reader has established that a SC is in
place the power up sequence can start at the SC
reader convenience. After the power up sequence, the
10 SC reader will provide first a clock to the SC and
then will release its reset signal. The SC is then
able to execute the stored Operating System (OS).
The SIM card is particular since it is put in place
only once with the power off and used constantly
15 subsequently to its positioning.

The first application ever to have deployed the
SC technology more than 20 years ago is the public
telephone system. The die size used in this
application is less than 1mm^2 . Just memories and
20 logic circuits are integrated in the IC. In 1999,
Pre-paid SC accounted for more than 2/3 of the 1.3
billion SCs produced worldwide. The SC reader
utilizes all eight contacts to interface properly
with the different SC generations. When a SC is
25 inserted in the payphone, the telephone
infrastructure authenticates the SC and the telephone
remove units out of the SC. It is worth noting that
the SC developed for Banking applications can be
utilized in a payphone. The payphone does not remove
30 units out of a Bank card but bills the SC carrier.

The second largest application using the SC has
been deployed by the Banking industry. The ATM and
POS infrastructures have been installed in most
countries other than the USA. The die size used in
35 this application is about 10mm^2 . A microcontroller

and its associated memories and software are integrated in the IC. The SC reader utilizes up to six contacts to interface properly with the different SC generations. When a SC is inserted in the ATM or the POS, the SC carrier is asked to authenticate himself with a PIN code. The SC can store anything like the balance of cash the owner got out of an ATM on a per week basis, the details of purchases he has done since the last closing date, etc. Based on this information, the authorization can be issued on the spot once the PIN has authenticated the debtor without any telephone calls to the bank. Ultimately Banks and Businesses perform the equalization using the telephone, private communication networks and some day the Internet. While performing the equalization, a black list of fraudulent SC may be stored in the POS or ATM. This scheme has been able to reduce the fraud level down to 0.02% of all the transactions equivalent money done with the SC from 0.2% when no IC was embedded in the card. The level of fraud using SC has been reduced by ten fold compared to the regular credit cards.

The third largest application using SCs has been deployed by GSM manufacturer. The die size used in a SIM is about 30mm². A microcontroller and its associated memories and software are integrated in the IC. The SIM reader utilizes five contacts to interface properly with the SC. The most sophisticated SC applications are performed in GSM using Java applets.

A whole new market for the SC is now emerging with the Internet accessed from a Personnel Computer. Secure message, Public Key Infrastructure, Authentication and Electronic Payment are the new SC hot areas. The SC can be an e-commerce facilitator.

The differentiation of the smartcard compared to other solutions is to have the PIN in the memory that is never communicated in any transaction.

Up to now, the SC is used in a SC reader
5 connected to the computer. Two protocols are
involved in supporting transactions between the SC
and the application run by the computer. The first
protocol complies with the ISO-7816-3. This standard
provides detailed requirements for the serial
10 interface between SC and SC reader. The reader is
connected to the computer by via a Serial Port, a
Parallel Port or even the Universal Serial Bus [USB]
using a second protocol. The SC reader contains
electronic circuits and embedded software that enable
15 communication between the SC using the first protocol
and the computer using the second protocol. The
computer is loaded with the appropriate driver to
support the SC reader. Many countries have started
to use the SC in the PC environment. The die size
20 used in this application will be anywhere from 5mm² to
30mm². A microcontroller and its associated memories
and software are integrated in the IC with a
cryptocontroller. Sometimes, a bio-sensor will be
also integrated. The SC reader utilizes at least
25 five contacts to interface properly with the SC.

Closed infrastructures enabling all kinds of
transactions like Healthcare, Public phone, parking,
Loyalty programs, Cash payments, Credit payments are
using millions of ISO compliant SC readers around the
30 world. Europe has lead the development of these
technologies back in the late 1970's. In these
proprietary infrastructures, every single SC reader
is designed to carry many transactions each hour.
The many users share the cost of the SC reader.

35 The extreme growths of the e-commerce and

Internet transactions have highlighted the huge needs to secure transactions. Fraud is booming. False credit card numbers are used, credit card numbers are stolen and eavesdropping on the Internet is well established. Dotcom companies search for the device having the best cost/performance ratio. The SC is an excellent contender if the SC reader price can be reduced.

The USB has recently become firmly established and has gained wide acceptance in the Personal Computer (PC) marketplace. The USB has been developed in response to a need for a standard interface that extends the concept of "plug and play" to devices external to a PC. It has enabled users to install and remove external peripheral devices without having to open the PC case or to remove power from the PC. The USB provides a low-cost, high performances, half-duplex serial interface that is easy to use and readily expandable. The USB can be seen as a set of four wires carrying the power supply with two wires and data with the two other wires. The USB is currently defined by the Universal Serial Bus Specification written and controlled by USB Implementers Forum, Inc., a non-profit corporation founded by the group of companies that developed the USB Specification.

In particular, Chapter 5 USB Data Flow Model, Chapter 7 Electrical, Chapter 8 Protocol Layer and Chapter 9 USB Device Framework of Universal Serial Bus Specification are incorporated herein by reference. The increasingly widespread use of the USB in computers has led SC reader manufacturers to develop USB interfaces for connection of their products to computers to complement the existing serial and parallel interfaces.

We are now in a situation where the brick and mortar companies and the Banks have been using the SC technology for more than 15 years. On the other hand, the Internet, a formidable arena to enhance commerce and Banking activities, does not use the SC technology. Most of the Internet transactions are done from a PC and despite PC manufacturer efforts, the PC industry has failed to install on each PC a cost effective SC reader meeting the specific needs of web related applications. A comprehensive solution, servicing the needs of both the one already engaged in the SC technologies and those wishing to benefit from it, is to be found. These two fields should share a common authentication platform in the best interests of the customers and the service providers.

An example of a conventional approach may be found in published PCT application WO 99/49415 and entitled "Versatile Interface Smart Card." The system discloses a smart card system which can be used with different protocols. Specifically, the system provides a mode signal at one of the non-ISO standard contacts to indicate the protocol of the device that the card is communicating with. However, the mode signal is not checked until after the smart card is powered up and the reset signal has been applied. In other words, the smart card is already operating in the ISO 7816 protocol, and upon detection of the mode signal, may have to switch to a non-ISO protocol.

Summary of the Invention

In view of the foregoing background, it is therefore an object of the invention to provide an integrated circuit which can selectively operate in

accordance with more than one protocol.

It is a further object of the invention to provide a smart card system that can determine whether the smart card is communicating with an
5 interface using the ISO 7816 protocol or non-ISO protocol, and configure the smart card in such a protocol.

This and other objects, features and advantages in accordance with the present invention are provided by a multi-mode IC for operating in an ISO mode in accordance with International Standards Organization
5 7816 (ISO 7816) protocol, and a non-ISO mode, such as a USB mode in accordance with Universal Serial Bus (USB) protocol. The multi-mode IC includes a microprocessor and an external interface. The external interface includes a voltage supply pad, a
10 ground pad, a first set of pads in accordance with the first protocol, such as a reset pad, a clock pad and an input/output pad in accordance with the ISO 7816 protocol, and a second set of pads in accordance with the non-ISO protocol, such as a D-plus pad and a
15 D-minus pad in accordance with the USB protocol. The IC also includes a mode configuration circuit comprising a mode detector connected to one of the pads of the first set of pads, e.g. the clock pad, a USB voltage detector connected to the voltage supply
20 pad, a latching circuit connected to the switching block and an receiving output from the mode detector. The IC may also include a control register connected to the latching circuit for storing a mode configuration indicator.

25 Also, if the non-ISO mode is the USB mode, then the IC may include a USB cable detector connected to D-plus and D-minus pads. Here, the mode configuration circuit configures the IC to operate in one of the

0986337 104100

ISO and USB modes while disabling the other of the
ISO and USB modes, such that the reset, clock and
input/output pads are disabled when the switching
block is configured in the USB mode, and the D-plus
5 and D-minus pads are disabled when the switching
block is configured in the ISO mode. Since an ISO
transaction may occur while the power supply voltage
is within the range of 2.7 to 5.5 Volts, and a USB
transaction may occur while the power supply voltage
10 is within the range of 4.01 - 5.5 Volts, a voltage
detector may be provided to detect whether a power
supply voltage on the voltage supply pad can support
USB transactions.

A system using such an IC in accordance with the
15 present invention includes an ISO-compliant reader
and a non-ISO-compliant reader. Of course the ISO-
protocol reader would provide the necessary clock
signal at the clock pad of the IC. However, the non-
ISO-compliant reader includes a mode indication
20 circuit which provides one of the first set of pads,
e.g. the clock pad, with a mode indication signal.

A method aspect of the present invention
includes operating a multi-mode smart card in an ISO
mode in accordance with International Standards
25 Organization 7816 (ISO 7816) protocol, and a non-ISO
mode in accordance with a non-ISO protocol. The
multi-mode IC includes an external interface having a
voltage supply pad, a first set of pads in accordance
with the ISO protocol, and a second set of pads in
30 accordance with the non-ISO protocol. The method
comprises detecting whether one of an ISO-mode
condition and a non-ISO-mode condition exists on one
pad of the first set of pads during a power-on-reset
of the multi-mode IC; configuring the multi-mode IC
35 in the ISO mode and disabling the second set of pads

when the ISO-mode condition is detected; and
configuring the multi-mode IC in the non-ISO mode and
disabling the first set of pads when the non-ISO-mode
condition is detected. The method may also include
5 verifying the non-ISO mode, when the non-ISO-mode
condition is detected, by detecting a non-ISO-mode
voltage on the voltage supply pad.

Preferably, the first set of pads comprises a
reset pad, a clock pad and an input/output pad in
10 accordance with the ISO 7816 protocol, and detecting
whether the ISO-mode or non-ISO-mode condition exists
comprises detecting if a signal from one of an ISO-
compliant interface and a non-ISO-compliant interface
is present on one of the first set of pads, e.g. the
15 clock pad. The non-ISO protocol may comprise the
Universal Serial Bus (USB) protocol. Also, the
method may include storing a mode configuration
indicator for indicating whether the multi-mode IC is
configured in the ISO or non-ISO mode.

20 In the present invention, the IC is configured
in the ISO mode if an ISO condition is detected on
one pad of the first set of pads, such as the clock
pad. A mode indication signal may be provided on the
clock pad from a non-ISO-compliant reader. If so,
25 then the IC is configured in the non-ISO mode, such
as the USB mode. If the non-ISO mode is detected via
the clock pad during the power-on reset sequence,
then the USB voltage is verified on the voltage
supply pad, then a detection for USB connections to a
30 host may be performed before the IC is configured in
the USB mode. The IC is either configured in the ISO
or non-ISO mode depending on the signal level at the
clock pad during the power-on reset sequence. Once
the IC is configured in one mode, it can only operate
35 in that mode and it cannot be changed except via

another power-on reset sequence.

Brief Description of the Drawings

FIG. 1 is a schematic diagram of a smart card according to the present invention.

5 FIG. 2 is a schematic diagram of a personal computer having a smart card reader in accordance with the present invention.

FIG. 3 is a schematic diagram of a multi-mode IC and smart card system according to the present
10 invention.

FIG. 4 is a flowchart generally illustrating the steps of a method of operating the multi mode IC of the present invention.

FIG. 5 is a schematic diagram illustrating the
15 SC with the lead frame contacts.

FIG. 6 is a schematic diagram illustrating the electromechanical switch detecting that a SC is inserted in a SC reader.

FIGs. 7A and 7B are schematic diagrams
20 illustrating an IC attached to an ISO lead frame and wire bonded to the lead frame contacts.

FIG. 8 is a table showing which SC is using which lead frame contacts.

FIG. 9 is a schematic diagram illustrating the
25 prior art ISO SC reader.

FIG. 10 is a schematic diagram illustrating a USIC module.

FIG. 11 is a schematic diagram illustrating a USIC or an ISO SC compatible with the ISO SC reader.

30 FIG. 12 is a schematic diagram illustrating the ISO signals with the position switch activated by the SC insertion.

FIG. 13 is a timing diagram showing the ISO signals referenced to the position switch activated.

098837 10100

FIG. 14 is a schematic diagram illustrating a USIC inserted in an ISO SC reader selecting the mode using CLK signal.

FIG. 15 is a schematic diagram illustrating a
5 USIC inserted in an ISO SC reader selecting the mode using I/O signal.

FIG. 16 is a schematic diagram illustrating a USIC inserted in an ISO SC reader selecting the mode using VPP signal.

10 FIG. 17 is a timing diagram showing the MODE signals after power up when USIC is used in an ISO SC reader.

FIG. 18 is a schematic diagram illustrating the USB virtual reader and the USIC or USC.

15 FIG. 19 is a schematic diagram illustrating the USIC used with an USB virtual reader.

FIG. 20 is a timing diagram showing the signals involved during the power up sequence when USIC is inserted in an USB virtual reader.

20 FIG. 21 is a schematic diagram illustrating the USIC inserted in an USB virtual reader selecting the mode using C3 signal.

FIG. 22 is a schematic diagram illustrating the USIC inserted in an USB virtual reader selecting the
25 mode using C7 signal.

FIG. 23 is a schematic diagram illustrating the USIC inserted in an USB virtual reader selecting the mode using C6 signal.

FIG. 24 is a timing diagram showing the MODE
30 signals after power up when USIC is used in an USB virtual reader.

FIG. 25 is the flow diagram illustrating the general steps performed aboard a bi-mode, ISO and USB, device to select one MODE and start the CPU.

35 FIG. 26 is a schematic diagram illustrating the

098637-1010

IC attached to the lead frame and wire bonded to the lead frame contacts for an USC.

FIG. 27 is a schematic diagram illustrating the SIM plug ready to be separated from a USIC or a USC.

5 FIG. 28 is a schematic diagram illustrating the SIM plug inserted in a token compatible with a series A USB plug.

Detailed Description of the Preferred Embodiments

10 The present invention will now be described more fully hereinafter with reference to the accompanying drawings, in which preferred embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth
15 herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like numbers refer to like elements throughout.

20 Referring to FIG. 1, a smart card **10** in accordance with the present invention will now be described. The smart card **10** is made of plastic, for example, and has a plurality of electrical contacts or pads **12** on an outer surface thereof, as would be
25 appreciated by those skilled in the art. As shown, the card **10** includes eight pads **12**, for example. The pads **12** are the external interface for the integrated circuit (IC) **11** which is embedded within the card **10** and typically beneath the pads. The size of the card
30 **10** and the position of the pads **12** are determined by appropriate standards such as ISO 7816 discussed above. Of course the IC **11** can also be embedded in other media such as the Subscriber Identity Module

(SIM) for mobile phones.

A personal computer (PC) **20**, as shown in FIG. 2, typically includes a central processing unit (CPU) and various input/output devices such as a monitor, keyboard and a mouse. Additionally, the PC **20** includes a smart card reader **22** which may, for example, be used to control access to the PC. As shown, the smart card reader **22** is a separate peripheral device; however, the smart card reader could also be incorporated into the CPU housing or the keyboard, for example.

The smart card reader **22** may conform to the ISO 7816 protocol or a non-ISO protocol such as the Universal Serial Bus (USB) protocol as discussed above. The ISO 7816 protocol is the conventional standard for use in smart cards and includes a voltage supply pad **VCC**, a ground pad **GND**, an input/output pad **I/O**, a reset pad **RST** and a clock pad **CLK**. The ISO protocol is characterized by an Answer-to-Reset (ATR) sequence when a power-on-reset or hardware reset is applied to the IC **11**.

The USB protocol is currently being used to replace the different PC **20** interfaces for peripheral devices such as the mouse, keyboard, serial I/O port etc. As discussed above, the USB protocol can be hot plug and play which means that a USB protocol device can be connected or disconnected from the PC **20** without necessitating a reboot. The USB cable includes a voltage supply wire **VBUS**, a ground wire **GND**, a D-plus wire **D+** or **DP** and a D-minus wire **D-** or **DM**. The differential signal on **D+** and **D-** is a data stream in NRZI coding. The USB 1.1 specification requires the power supply of a USB device to be between 4.01V and 5.5V.

As set forth previously, it is desirable to provide a smart card system that can operate in the ISO 7816 protocol and another non-ISO protocol, such as the USB protocol, depending on the type of reader the card is communicating with. Thus, referring to FIG. 3, an embodiment of the present invention will be described. A multi-mode IC **11** is capable of operating in first mode such as an ISO mode in accordance with International Standards Organization 7816 (ISO 7816) protocol, and a second non-ISO mode such as a USB mode in accordance with Universal Serial Bus (USB) protocol. The multi-mode IC **11** operates selectively in one mode or the other, but not both simultaneously.

The multi-mode IC **11** is preferably in the smart card **10** and includes a microprocessor **14**, a switching block **16**, and the external interface **12**. The external interface **12** comprises a voltage supply pad **VCC**, a reference voltage/ground pad **GND**, a first set of pads for the ISO mode, and a second set of pads for the non-ISO mode. The first set of pads preferably include a reset pad **RST**, a clock pad **CLK** and an input/output **I/O** pad in accordance with the ISO 7816 protocol. The second set of pads preferably includes a D-plus pad **D+** and a D-minus pad **D-** in accordance with the USB protocol.

Because the IC **11** can only operate in one of the two modes which have different external interfaces, the IC will need to determine in which mode to operate. Thus, the IC **11** includes a mode configuration circuit **18** comprising a mode detector **49** connected to one of the ISO pads, such as the clock pad **CLK**. The mode configuration circuit **18** may also include a USB voltage detector **30** connected to

the voltage supply pad VCC for detecting a non-ISO mode voltage supply such as the USB voltage, a latching circuit **40** connected to the switching block and receiving outputs from the mode detector **49** and a
5 USB host connection detector **35**, for storing a mode configuration indicator and the USB_RST starting signal.

At least for the case where the non-ISO mode is the USB mode, the mode configuration circuit **18** may
10 include the USB host connection detector **35** connected to the D-plus and D-minus pads, and providing an output to the latching circuit **40**. The USB host connection detector **35** may be used to verify that the medium including the IC **11** is actually connected to a
15 USB port once the IC has been configured in the NISO mode.

During the start-up or power-on sequence of the IC **11**, the mode configuration circuit **18** configures the IC **11** to operate in one of the ISO and non-ISO
20 modes while disabling the other mode. For example, the reset pad **RST**, clock pad **CLK** and input/output **I/O** pad are disabled when the IC **11** is configured in the USB mode, and the D-plus pad **D+** and D-minus **D-** pad are disabled when the IC **11** is configured in the ISO
25 mode. To prevent any glitches, the detected mode is latched by the latching circuit **40**. The operating system of the IC **11** will then check this bit during the reset routine to access the appropriate code for the latched mode.

30 Accordingly, if the smart card **10** including the multi mode IC **11** is used with a typical smart card reader, it will operate as specified in the ISO 7816 protocol while the USB interface, i.e. the D-plus **D+**

and D-minus **D-** pads, is disabled to consume less power. However, because the IC **11** includes a USB interface, ISO 7816-like transactions can be performed using a low-cost USB device rather than an ISO-compliant smart card reader. Here, the ISO mode interface, i.e. the reset **RST**, clock **CLK** and input/output **I/O** pads, is disabled. Once the IC **11** is configured in one of the modes, it must stay in that mode until another power-on-reset.

10 Preferably, the mode detector **49** detects whether a signal on the clock pad **CLK** is less than about 30% of a voltage supply signal on the voltage supply pad **VCC**, and the mode configuration circuit **18** configures the IC **11** in the ISO mode if the signal on the clock pad **CLK** is less than about 30% of the voltage supply signal on the voltage supply pad **VCC**. Alternatively, the mode configuration circuit **18** configures the IC **11** in the USB mode if the signal on the clock pad **CLK** is not less than about 70% of the voltage supply signal on the voltage supply pad. If so, then the USB voltage detector **30** detects whether a power supply on the voltage supply pad **VCC** is greater than about 3.5 volts or preferably between about 4.01 and 5.5 volts to verify that the multi-mode IC **11** can communicating with a USB interface.

25 A system using such an IC **11** in accordance with the present invention includes a ISO-protocol reader and a USB-protocol reader. The ISO-protocol reader may be a conventional smart card reader that would provide the necessary clock signal at the clock pad of the IC. Thus, when a smart card **10** including the multi mode IC **11** is inserted into a conventional smart card reader, the mode configuration circuit **18**

configures the IC **11** in the ISO mode because the signal on the clock pad **CLK** would be less than about 30% of the voltage supply signal on the voltage supply pad **VCC**. However, a USB-protocol reader in accordance with the present invention includes a USB-mode indication circuit **70** which provides the clock pad CLK with a USB-mode indication signal, such as a fixed voltage level, which will be discussed in detail below. So, when the smart card **10**, or other medium, is connected to such a USB-protocol reader, the mode configuration circuit **18** configures the IC **11** in the NISO mode because the signal on the clock pad CLK would not be less than about 70% of the voltage supply signal on the voltage supply pad **VCC**.

A method aspect of the present invention will now be discussed while referring to FIG. 4. The method includes operating a multi-protocol smart card **10** in a first mode in accordance with an ISO protocol, and a second mode in accordance with a non-ISO protocol, such as the USB protocol. As discussed above, the multi-protocol smart card **10** includes an external interface **12** having a voltage supply pad **VCC**, a reference voltage/ground pad **GND**, a first set of pads **Clk**, **RST**, **I/O** in accordance with the ISO protocol, and a second set of pads, e.g. **D+**, **D-**, in accordance with the non-ISO protocol such as USB.

The method begins (block **120**) and a power-on-reset sequence of the IC **11** is started at block **122**. Then, at block **124**, the method includes detecting whether an ISO mode condition exists on one pad of the first set of pads during the power-on-reset of the multi-mode IC, or whether a non-ISO mode condition exists on the one pad of the first set of pads during the power-on-reset of the multi-mode IC.

For security and integrity of the IC **11**, the mode should be detected as soon as possible. In a preferred embodiment, it is detected whether a signal on the clock pad **CLK** is less than about 30% of a
5 voltage supply signal on the voltage supply pad **VCC**. If the signal on the clock pad **CLK** is less than about 30% of the voltage supply signal on the voltage supply pad **VCC**, the IC **11** is configured in the ISO mode and the second set of pads, e.g. **D+**, **D-**, in
10 accordance with the non-ISO protocol such as USB, is disabled (block **130**) by connecting them to **GND**, for example. Alternatively, if the signal on the clock pad **CLK** is not less than about 70% of the voltage supply signal on the voltage supply pad **VCC**, the IC
15 **11** is configured in the non-ISO or USB mode, and the first set of pads, i.e. **Clk**, **RST**, **I/O**, in accordance with the ISO protocol is disabled (block **128**) by connecting them to **GND**, for example.

Again, the method may include verifying the non-
20 ISO mode, when the non-ISO mode condition is detected at block **124**, by detecting a non-ISO mode voltage, e.g. a USB mode voltage, on the voltage supply pad **VCC** (block **126**) and detecting a USB host connection (block **136**). The method may include storing a mode
25 configuration indicator for indicating whether the multi-mode IC is configured in the ISO or non-ISO mode (block **132**) before ending at block **134**.

For example, the IC **11** is configured in the ISO mode if an ISO condition is detected on the clock pad
30 **CLK**. A mode indication signal may be provided on the clock pad **CLK** if the IC **11** is communicating with a virtual USB reader **22**. If so, then the IC **11** is configured in the USB mode. Also, if a USB interface

is detected via the clock pad **CLK** during the power-on reset sequence, then a detection for a USB cable may be performed, and the USB voltage is verified on the voltage supply pad **VCC** before the IC **11** is configured in the USB mode.

The IC **11** is either configured in the ISO or USB mode depending on the signal level at the clock pad **CLK** during the power-on reset sequence. To identify the non-ISO mode, such as USB, a fixed voltage level is applied to the clock pad **CLK**. This may be done at the reader and/or on the IC **11** using a pull-up resistor between **VCC** and **CLK**. The ISO 7816 power-on-reset sequence begins by applying the voltage supply to **VCC** and the reference voltage/ground to **GND** while the signals on **RST** and **CLK** are kept low or at "0". Then the **I/O** pad receives a signal from a pull-up resistor at the reader or on the IC **11** to put the IC in a receiving mode. Then a clock signal is provided on **CLK** and after a certain amount of time, the signal on **RST** is set high or at "1". This starts the IC's reset sequence. The signal is provided on **RST** when the reader is sure the IC **11** is in the power-on reset state and waiting for the reset sequence.

So, in sum, the clock signal on **CLK** begins at "0" and then is activated at a minimum time of 400 cycles before the signal on **RST** rises. Since a fixed voltage level is applied on **CLK** when the IC **11** is communicating with a USB device, if the signal detected on **CLK** is fixed at "1" (greater than 70% of VCC), then the IC is configured in the USB mode. If the signal on **CLK** is a clock signal alternatively greater than 70% of VCC and less than 30% of VCC, then the IC **11** is configured in the ISO mode. This

detection at block **124** can be a test of whether the signal on **CLK** is less than 30% of the signal on **VCC**. If so, then ISO mode. If not, then USB mode. Then, for USB detection, at block **126**, the voltage supply signal on **VCC** is checked to ensure it is greater than 4.01 Volts. According to the USB protocol, the voltage supply on **VCC** in the USB mode should be between about 4.01V and 5.5V.

Of course, other ISO pads, such as the reset pad **RST**, variable supply voltage **VPP**, and the input/output pad **I/O**, may also be used with varying degrees of complexity. Once the IC **11** is configured in one mode, it can only operate in that mode and it cannot be changed except via another power-on-reset sequence. To prevent any glitches, the detected mode is preferably latched and a mode indicator/bit is set. The operating system of the IC **11** will then check this bit during the microcontroller reset routine to access the appropriate code for the latched mode.

Thus, a multi-mode IC **11**, smart card **10**, system and associated method of operation in the ISO 7816 protocol and another non-ISO protocol, such as the USB protocol, have been described in accordance with the present invention. A medium, such as the smart card **10**, incorporating the multi-mode IC **11** can be used in a typical ISO compliant smart card reader or in a lower-cost virtual USB reader, such as a personal computer.

More specifically, the present invention will be described with reference to FIGs. 5-28. The present invention establishes a bridge between the brick and mortar field and the Internet. This is the Universal Serial Bus and ISO Smart Card (USIC) **110**. The USIC

110 is able to perform either transactions on an ISO SC reader 120 (FIG. 11) or transactions directly on a USB port 124 (FIG. 18). In the latter case the USIC 110 is really a USB device supporting amongst other
5 USB characteristics the suspend state. The very same USIC 110 may be used in a POS or in an ATM and also in surfing the web because the ISO SC reader burden has disappeared. For example, one person carrying a USIC 110 can use it to shop on his favorite Internet
10 sites through the USB protocol and use it to get cash from the ATM with the ISO protocol. The same portable device services two needs. To furthermore embrace possible applications dedicated to the PC environment a SC with only a USB interface 120' (FIG.
15 26) is also available (USC).

The USB SC reader interface is partly included in the USC or the USIC and partly included in the PC. The IC 1100 used in a USIC 110 can handle either the USB protocol or the ISO protocol while performing the
20 same application. Both USC and USIC interface with the USB with a simple passthrough connector. Beside the passthrough connector and few decoupling capacitors, USC and USIC does not required any other electronic circuits to be seen as a bus powered
25 device 143 on the USB by the USB host controller 121. When a USIC reader 140 is connected to a USB port without the USIC being inserted, the application does not see the reader. This is a virtual USIC reader 140. The USIC reader connected on the USB accepts
30 also USC.

The passthrough connector establishes electrical links between the USB signals on the USB port 124 and the USC or USIC contacts in the virtual reader 140. When there is no card in this virtual reader 140 the

system does not see any SC reader. When the USC or the USIC is inserted into the virtual reader **140**, the system sees the virtual reader once the USB device has been enumerated.

5 This invention relates to methods and devices enabling USB transactions when a USIC or a USC is used in a virtual USB SC reader and at the same time these methods and devices enable ISO transactions when a USIC is used in an ISO SC reader. The field
10 of the invention is that of authentication devices and more specifically SC, Token and IC carrying more than one serial interface such as USB and ISO and authentication devices and more specifically SC, token and IC carrying USB interface only.

15 An ISO reader **120** (FIG. 9) is recognized by the hardware platform using it even when no SC is inserted. The SC needs to be inserted in order for the protocol to start. No electrical signals are applied to the SC until the SC turns on a position
20 switch, which tells the platform that a SC is mechanically in place. A reader used in Payphone, POS or in ATM must comply with all the protocols used by different SC generations to insure legacy. Different SCs can be used in a reader. Both
25 synchronous and asynchronous SCs have obliged reader manufacturer to design interface transceiver on each ISO contacts except the power supply contacts (FIG. 8). The ISO 7816-2 requires up to eight connections between the SC reader and the ISO SC lead frame.
30 Contact C1 is assigned to the Supply voltage VCC, contact C2 is assigned to the Reset signal RST, contact C3 is assigned to the Clock signal CLK, contact C5 is assigned to the GND reference voltage, contact C6 is assigned to the Variable supply voltage
35 VPP and contact C7 is assigned to Data input/output

I/O. In synchronous ISO7816-10 applications, under type 2 operating conditions, contact C4 is assigned to function code FCB and contact C8 may also be used for other synchronous applications. An asynchronous SC under class B operating conditions does not require VPP voltage on C6. An asynchronous SC under class A operating conditions does require VPP voltage on C6. A synchronous SC under specific operating conditions may assign C8 to a fuse zapping capability. Furthermore, each reader contacts, beside VCC and GND, may have passive networks equipped with anti Electro-Static Discharge (ESD) circuits to VCC and GND to protect the IC against ESD during the SC insertion phase. Then, all eight ISO 7816-2 interface contacts have been assigned specific characteristics with active or passive networks.

Once the SC is in place, a switch informs the reader interface that the SC is in place. The powering up sequence may start. As described in the ISO7816-3, the SC reader interface circuit applies VCC and then, at the SC reader earliest convenience, the interface circuit applies the Clock (CLK) signal and after no less than 400 CLK cycles the Reset (RST) signal is released. The SC answers to the reader RST signal by sending an Answer To Reset (ATR) after 400 CLK cycles and before 40000 CLK cycles to the reader. The link is established and any transactions may start.

The SC of the present invention is compatible for use in USB applications. The USB requires four wires. For a USIC or USC, VBUS and GND can be dispatched respectively to the lead frame contacts C1 and C5. This is a minor change since in ISO7816-2, C1 is dedicated to VCC and C5 is dedicated to GND.

USIC needs to select its NISO mode until a power off sequence comes, and support USB transactions including suspend mode. When inserted in a USB virtual reader **140**, a USC will support USB transactions including suspend mode.

To summarize, SC, USIC and USC devices have to comply with the following rules:

1. A USIC has to select the ISO mode of operation when inserted in an ISO reader.
2. A USIC has to select the NISO mode of operation when inserted in an USB virtual reader.
3. A USC is by default in NISO mode and will support USB transactions when inserted in a USB virtual reader.
4. A USC is not damaged when inserted in an ISO reader.
5. A SC is not damaged when inserted in an USB virtual reader.

The mode selection process uses at least one contact. C2 is used at two logic levels in ISO, C3 is driven at zero or by a clock in ISO, C4 may be connected to zero by the interface in ISO and is not available in USB, C6 should be forced to zero by the USB interface, since it may be forced at VPP by the ISO interface, C7 should be forced to zero by the USB interface, since it may be pulled up by the ISO interface and C8 may be connected to zero by the ISO interface and is not available in USB. C3, C6 and C7 may be used to select the mode in which a USIC is going to perform.

Because of the nature of the smart card, inserted and removed once the transaction is complete many times a day for example, there is a need for USIC or USC to detect if it is properly inserted

before starting the CPU when used in an USB virtual reader **140**. Not only the proper voltage must be applied to the IC **1100** but the link between the device C4 and C8 and the host D+ and D- established.

5 Once the device is physically connected to the host **121**, it may attach itself to the USB.

The present invention is implemented to solve the foregoing tasks. It includes a method or a device, which sets the USIC, and more generally the
10 IC used in a USIC device in the mode matching the reader characteristics in which it is inserted. When an USIC is inserted in an ISO reader the USIC is working in ISO and the RST signal supplied by the SC reader interface starts the microcontroller. When an
15 USIC is inserted in a USB virtual reader **140**, the USIC is working in a non-ISO (NISO) and the reset signal for the microcontroller is generated using D- or D+ signals in conjunction with a Low Voltage Detection. When an USC is inserted in a USB virtual
20 reader **140**, the USC is working in NISO and the reset signal for the microcontroller is generated using D- or D+ signals in conjunction with a USB voltage detector.

The control logic of the IC **1100** used in USIC
25 performs the following tasks in a first preferred embodiment:

detects if an appropriate first power supply voltage is applied to the IC;
detects if any CLK is applied to the C3 pin of
30 the IC while it is pulled up by a load to C1,
if the CLK is applied or stays at zero, the mode is ISO else the mode is NISO;
stores the result in a MODE register;
if the IC is latched in the ISO mode, the pin

RST starts the microcontroller, which check the MODE register content and all transactions are performed as specified in ISO-7816 standards;

5 if the IC is latched in the NISO mode, the voltage present on C1 is checked to be greater than a second minimum power supply voltage specified by the USB specification greater than the first voltage and if it is so, the control logic detects if the pins D- or D+ are pulled down by the USB host 15k Ω pull down resistors after a defined settling delay, else nothing happens until the voltage becomes greater than the acceptable limit;

10

15 if the pins D- or D+ are pulled down by the USB host 15k Ω pull down resistors this information is stored in a USB_RST register and the control logic of the IC authorizes the microcontroller to start, The microcontroller reads MODE register content and the program enters the USB subprogram;

20

the subprogram waits an appropriate time such that the attachment of the device may be effective before 100ms after the good supply voltage has been detected, as described in the USB specification, the microcontroller checks if the pins D- or D+ are pulled down by the USB 15k Ω loads by reading the actual status of the connections. If the connections are established the device attach itself to the USB by connecting a pull up resistor on D- for a low speed device and D+ for a full speed device on one side and to an internal 3.3Volt voltage reference on the other side in

25

30

35 compliance with the USB specifications and all

09686327 104400

transactions are performed as specified in USB specifications. If this is not the case the microcontroller goes in MUTE and waits for a new power up sequence.

5 When a USIC or a USC is inserted into an USB
virtual reader **140**, the Smart Card interface must be
able to detect that it is used in USB and start an
adapted power up sequence compliant with the USB
specification. When a USIC is inserted into an ISO
10 reader **120**, the Smart Card interface must be able to
detect that it is used in ISO and start an adapted
power up sequence compliant with the ISO
specification.

When a SC **110** (FIG. 5) equipped with a module
15 **120** having contacts **115**, and possibly a magnetic
strip **112** and an embossed area **114**, is inserted in a
SC reader (FIG.6) guided by **131** a switch **130** stops
the SC and signals that a SC is inserted. The SC **110**
is carrying a module **120** (FIGs.7A and 7B) where all
20 eight ISO contacts C1-C8 are at the opposite of a
lead frame **111**. An IC **1100** is attached to the lead
frame **111**. Electrical connections between the IC **1100**
and the lead frame contacts are done using wire
bonding techniques **109**. A mechanical and chemical
25 protection will complete the packaging of this less
than 200 μ m-thickness structure.

Turning now to FIG. 8, there is a table listing
which contacts synchronous and Asynchronous
applications are using. Il application are still in
30 use for prepaid SC. On the same table we have listed
the present applications USIC and USC and how are
assigned the contacts described in ISO7816-2 to the
module embedded in these cards.

5

10

Turning now to FIG. 11, there is shown an ISO SC reader **120** handling ISO SC, or USB compliant SC such as USIC or USC.

15

25

30

FIG. 16 represents another embodiment of the invention where the IC **1100** has a pull up resistor **190** on C6 inside the IC **1100**. **192** is a non inverting

Schmitt trigger. The USIC is in an ISO SC reader.

FIG. 17 summarizes what is happening in the three above embodiments. Embodiment of FIG. 14, when VCC is set on C1 a signal Badpwr is set to "1" until
5 the voltage VCC is above a certain limit, example 2.8 Volt, for at least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s (dt) more. The CLK type 1 signal is applied, and if during dt the signal at the
10 input of **192** goes to "0" the latch **195** is reset and MODE is forced to "0" by the set on **196**. If the CLK type 2 signal is applied, during dt the signal at the input of **192** goes to "0" the latch **195** is reset and MODE is forced to "0" by the set on **196**. For both
15 clock signals, dt must be greater than the half period of the largest period, 1 μ s, allowed on C3.

The embodiment of FIG. 15, when VCC is set on C1 a signal Badpwr is set to "1" until the voltage VCC is above a certain limit, example 2.8 Volt, for at
20 least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s more. The C7 contact is having a weak pull up resistor outside because of the ISO protocol but also inside to be sure that there is a pull up. If during
25 dt, the signal at the input of **192** stays at "1" the latch **195** is reset and MODE is forced to "0" by the set on **196**. The embodiment of FIG. 16, when VCC is set on C1 a signal Badpwr is set to "1" until the voltage VCC is above a certain limit, example
30 2.8 Volt, for at least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s more. The C6 contact is having a voltage VPP driving it because of the ISO protocol but is having also a pull resistor **190**, if

during dt the signal at the input of **192** stays at "1"
the latch **195** is reset and MODE is forced to "0" by
the set on **196**.

Turning now to FIG. 18, it represents a virtual USB reader **140** with its passthrough connector **127'**, its USB cable **142** and the USB series A plug connector **141**. USC and USIC are compliant with this reader. The virtual reader **140** is connected to the USB port **124** of the host PC **121**. The SC **1200** inserted in the virtual reader **140** forms a USB device **143**. Turning now to FIG. 19, passthrough contacts **180** mate with module contacts. There is no action of the SC telling the SC reader to apply voltages. The embarked system on the chip **1100** not only must select the mode NISO but it must be sure also to start the microcontroller in an appropriate manner since there is no reset signal. The pin C6 and I/O are connected to GND since that is the only possibility for them if they are used to detect the mode NISO, and the pin C3 may be connected to VBUS. The internal pull-up resistor is preferable since it avoids any rebound between the contact and the pin.

Turning now to FIG. 20, is represented all the signals involved in a NISO detection. VCC is applied to the USIC or USC at t0. Badpwr will set CUSBPD at t2. By the time being the card insertion process is ongoing and at some point the contact C4 and C8 will be connected to the pull down resistors **1122** and **1123** in the host. Signals "D - in place" and "D + in place" represent the fact that the SC contacts are touching the interface contacts while bouncing. The CUSBPD FIG. 21 signal delivers a current to the resistors **1122** and **1123** calibrated by **1103** and **1104**. The resulting voltages on D- and on D+ are monitored

by comparators **1112**, **1113**, **1114** and **1115**. The voltage divider is such that when both the voltage on D- and on D+ are below the voltage on the upper side of the resistor **1110** and above the voltage on the lower side of that same resistor the AND **1116** delivers USBPD t5 and resets **1119** to generate USB_RST at t7. The generated voltages across resistors **1122** and **1123** are less than a VIH of 2.8 Volts such that it is not interpreted by the host as an attachment which occurs at t12. The RST of the CPU **1121** is released because the switching block is as per MODE=1. The CPU has started and initializes itself, reads MODE and performs transactions in USB until there is a power off sequence. Later, but before the 100 ms limit set by the USB specification, the CPU check if the USBPD at t8 is at "1". If so the device disables CUSBPD. The device attaches itself on the USB by ATTACH at t12 by connecting the pull up device **1101** to the 3.3Volt using **1102**. The host drives the USB with the single ended zero (SE0) signal after t13. During t14 the enumeration of the device starts.

Turning now to FIG. 24, it summarizes what is happening in the three embodiments. The preferred embodiment of FIG. 21, when VCC is set on C1 a signal Badpwr is set to "1" until the voltage VCC is above a certain limit, example 2.8 Volt, for at least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s more. The contact C3 is at "1" because of the routing inside the virtual reader FIG. 19, not connected, and because of the pull up resistor **190**. Bouncing on C3 does not disturb this embodiment. If during dt the signal at the input of **192** stays to "1" the latch **196** is reset by Q **195** and MODE = 1 = NISO. In the

embodiment of FIG. 22, when VCC is set on C1 a signal Badpwr is set to "1" until the voltage VCC is above a certain limit, example 2.8 Volt, for at least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s more. The C7 contact is connected to the ground outside the virtual reader, if during dt the signal at the input of **192** stays at "0" the latch **196** is reset by Q **195** and MODE = 1 = NISO. In the embodiment of FIG. 23, when VCC is set on C1 a signal Badpwr is set to "1" until the voltage VCC is above a certain limit, example 2.8 Volt, for at least a certain period of time, example 500 μ s. Badpwrwd is the same signal which last approximately 4 μ s more. The C6 contact is connected to the ground outside the virtual reader, if during dt the signal at the input of **192** stays at "0" the latch **196** is reset by Q **195** and MODE = 1 = NISO.

Turning now to FIG. 25, a flow diagram of a USIC process is depicted. In FIG. 26, a USC module is represented. In that case the MODE is forced at 1. When this module is used in an ISO reader nothing happens. In an USB virtual reader, the IC will start in USB following the procedure described on FIG. 20.

FIG. 27 shows a SIM card **1400** ready to be removed from the SC. The SIM card **1400** may embed a USIC or a USC module **110**. Turning now to FIG. 28, a different form factor for the USB virtual reader depicted in FIG 18 is shown. **1500** is a token reader. The SIM card **1400** is inserted in a passthrough connector **127'** but not using any cable. The series A plug **141** is directly connected to the passthrough connector.

Many modifications and other embodiments of the invention will come to the mind of one skilled in the

5

THAT WHICH IS CLAIMED IS:

1. A multi-mode integrated circuit (IC) for operating in an ISO mode in accordance with International Standards Organization 7816 (ISO 7816) protocol, and a non-ISO mode in accordance with a non-ISO protocol, the multi-mode IC comprising:
 - a microprocessor;
 - an external interface connected to the microprocessor and comprising
 - a voltage supply pad,
 - a ground pad,
 - a first set of pads in accordance with the ISO 7816 protocol, and
 - a second set of pads in accordance with the non-ISO protocol; and
 - a mode configuration circuit connected to the switching block for configuring the multi-mode IC in one of the ISO mode and the non-ISO mode based upon a signal on one pad of the first set of pads.
2. A multi-mode IC according to Claim 1 wherein the mode configuration circuit configures the multi-mode IC to operate in one of the ISO and non-ISO modes while disabling the other of the ISO and non-ISO modes.
3. A multi-mode IC according to Claim 2 wherein the first set of pads is disabled when the multi-mode IC is configured in the non-ISO mode, and the second set of pads is disabled when the multi-mode IC is configured in the ISO mode.
4. A multi-mode IC according to Claim 1 wherein the mode configuration circuit comprises:

a mode detector connected to the one pad of the first set of pads; and

a latching circuit connected to the microprocessor and receiving an output from the mode
5 detector.

5. A multi-mode IC according to Claim 4 further comprising a control register connected to the latching circuit for storing a mode configuration indicator.

6. A multi-mode IC according to Claim 4 further comprising a voltage detector connected to the voltage supply pad to detect a voltage supply of one of the ISO and non-ISO modes.

7. A multi-mode IC according to Claim 4 wherein the non-ISO mode comprises a Universal Serial Bus (USB) mode, and the second set of pads includes D-plus and D-minus pads in accordance with the USB
5 protocol; and further comprising a USB cable detector connected to the D-plus and D-minus pads.

8. A multi-mode IC according to Claim 4 wherein the first set of pads includes a clock pad, a reset pad, and an input/output pad in accordance with the ISO 7816 protocol.

9. A multi-mode IC according to Claim 4 wherein the first set of pads includes a clock pad, a reset pad, a variable supply voltage pad, and an input/output pad in accordance with the ISO 7816
5 protocol; and wherein the mode detector comprises a pull-up resistor connected to the one pad of the first set of pads.

09686327 101100
00000000 00000000

10. A multi-mode smart card for operating in an ISO mode in accordance with International Standards Organization 7816 (ISO 7816) protocol, and a non-ISO mode in accordance with a non-ISO protocol, the
5 multi-mode smart card comprising:

a card body; and

a multi-mode integrated circuit (IC) carried by the card body and comprising

an external interface including

10 a voltage supply pad,

a ground pad,

a first set of pads in accordance with the ISO 7816 protocol, and

15 a second set of pads in accordance with the non-ISO protocol, and

a mode configuration circuit for configuring the multi-mode IC in one of the ISO mode and the non-ISO mode and comprising

20 a mode detector connected to one pad of the first set of pads, and

a latching circuit connected to the mode detector.

11. A multi-mode smart card according to Claim 10 further comprising a control register connected to the latching circuit for storing a mode configuration indicator.

12. A multi-mode smart card according to Claim 10 further comprising a voltage detector connected to the voltage supply pad to detect a voltage supply of one of the ISO and non-ISO modes.

096633 101100

13. A multi-mode smart card according to Claim 10 wherein the non-ISO mode comprises a Universal Serial Bus (USB) mode, and the second set of pads includes D-plus and D-minus pads in accordance with the USB protocol; and further comprising a USB cable detector connected to the D-plus and D-minus pads.

14. A multi-mode smart card according to Claim 10 wherein the mode configuration circuit configures the multi-mode IC to operate in one of the ISO and non-ISO modes while disabling the other of the ISO and non-ISO modes.

15. A multi-mode smart card according to Claim 14 wherein the first set of pads is disabled when the multi-mode IC is configured in the non-ISO mode, and the second set of pads is disabled when the multi-mode IC is configured in the ISO mode.

16. A multi-mode smart card according to Claim 10 wherein the first set of pads includes a clock pad, a reset pad, and an input/output pad in accordance with the ISO 7816 protocol.

17. A multi-mode smart card according to Claim 10 wherein the first set of pads includes a clock pad, a reset pad, a variable supply voltage pad, and an input/output pad in accordance with the ISO 7816 protocol; and wherein the mode detector comprises a pull-up resistor connected to the one pad of the first set of pads.

18. A multi-mode smart card system for operating in an ISO mode in accordance with International Standards Organization 7816 (ISO 7816)

protocol, and a non-ISO mode in accordance with a non-ISO protocol, the multi-mode smart card system comprising:

- 5 a multi-mode smart card comprising
 - an external interface including
 - a voltage supply pad,
 - a ground pad,
 - a first set of pads in accordance with the ISO 7816 protocol, and
 - 10 a second set of pads in accordance with the non-ISO protocol, and
 - a mode configuration circuit for configuring the multi-mode smart card in one of the ISO mode and the non-ISO mode and comprising
 - 15 a mode detector connected to one pad of the first set of pads, and
 - a latching circuit connected to the mode detector; and
 - a non-ISO-compliant smart card reader for
 - 20 reading the multi-mode smart card including
 - a smart card interface having a plurality of contacts for respectively mating with the voltage supply pad, the ground pad, and the second set of pads in accordance with the non-
 - 25 ISO protocol, and
 - a mode indication circuit for connection to the one pad of the first set of pads for providing a non-ISO mode indication signal to the mode detector of the mode configuration
 - 30 circuit.

19. A multi-mode smart card system according to Claim 18 wherein the mode configuration circuit further comprises a control register connected to the latching circuit for storing a mode configuration

indicator.

20. A multi-mode smart card system according to Claim 18 wherein the mode configuration circuit further comprises a voltage detector connected to the voltage supply pad to detect a voltage supply of one of the ISO and non-ISO modes.

21. A multi-mode smart card system according to Claim 18 wherein the non-ISO mode comprises a Universal Serial Bus (USB) mode, and the second set of pads includes D-plus and D-minus pads in accordance with the USB protocol.

22. A multi-mode smart card system according to Claim 18 wherein the mode configuration circuit configures the multi-mode IC to operate in one of the ISO and non-ISO modes while disabling the other of the ISO and non-ISO modes.

23. A multi-mode smart card system according to Claim 22 wherein the first set of pads is disabled when the multi-mode IC is configured in the non-ISO mode, and the second set of pads is disabled when the multi-mode IC is configured in the ISO mode.

24. A multi-mode smart card system according to Claim 18 wherein the first set of pads includes a clock pad, a reset pad, and an input/output pad in accordance with the ISO 7816 protocol.

25. A multi-mode smart card system according to Claim 18 wherein the first set of pads includes a clock pad, a reset pad, a variable supply voltage pad, and an input/output pad in accordance with the

ISO 7816 protocol; and wherein the mode detector comprises a pull-up resistor connected to the one pad of the first set of pads.

26. A method of operating a multi-mode integrated circuit (IC) in an ISO mode in accordance with International Standards Organization 7816 (ISO 7816) protocol, and a non-ISO mode in accordance with
5 a non-ISO protocol, the multi-mode IC including an external interface having a voltage supply pad, a ground pad, a first set of pads in accordance with the ISO protocol, and a second set of pads in accordance with the non-ISO protocol, the method
10 comprising:
detecting whether one of an ISO-mode condition and a non-ISO-mode condition exists on one pad of the first set of pads;
configuring the multi-mode IC in the ISO mode
15 and disabling the second set of pads when the ISO-mode condition is detected; and
configuring the multi-mode IC in the non-ISO mode and disabling the first set of pads when the non-ISO-mode condition is detected.

27. A method according to Claim 26 wherein
detecting whether one of the ISO-mode condition and the non-ISO-mode condition exists on the one pad of the first set of pads comprises detecting whether
5 one of the ISO-mode condition and the non-ISO-mode condition exists during a power-on-reset of the multi-mode IC.

28. A method according to Claim 26 further comprising verifying the non-ISO mode, when the non-ISO-mode condition is detected, by detecting a non-

ISO-mode voltage on the voltage supply pad.

29. A method according to Claim 26 wherein the first set of pads comprises a reset pad, a clock pad and an input/output pad in accordance with the ISO 7816 protocol.

30. A method according to Claim 29 wherein detecting whether the ISO-mode or non-ISO-mode condition exists comprises detecting if a signal from one of an ISO-compliant interface and a non-ISO-compliant interface is present on the clock pad.

31. A method according to Claim 26 wherein the first set of pads includes a clock pad, a reset pad, a variable supply voltage pad, and an input/output pad in accordance with the ISO 7816 protocol.

32. A method according to Claim 26 wherein the non-ISO protocol comprises a Universal Serial Bus (USB) protocol.

33. A method according to Claim 26 further comprising storing a mode configuration indicator for indicating whether the multi-mode IC is configured in the ISO or non-ISO mode.

Abstract of the Disclosure

5
10
15
20




FIG. 1




FIG. 2




FIG. 3




FIG. 4






FIG. 5




Conventional Applications					New applications		
	I1	I2	A1	A2	USIC	USC	
C1	VCC	VCC	VCC	VCC	VBUS	VBUS	
C2	used	used	RST	RST	RST		
C3	used	used	CLK	CLK	CLK		
C4	used	used			D +	D +	
C5	GND	GND	GND	GND	GND	GND	
C6	VPP	VPP	VPP				
C7	used	used	I/O	I/O	I/O		
C8	used				D -	D -	

ISO contacts

Plc-8

Prior art



ISO smart card

FIG. 9




FIG. 10




FIG. 11

ISO SC or
USB and ISO SC [USIC]

FIG. 12




FIG. 12

Ta: up to the interface
 $t_a \leq 200 / F$
 $t_b \geq 400 / F$
 $400 / F \leq t_c \leq 40\,000 / F$




Fig. 13




Fig. 14




FIG. 15





Fig. 17



USB SC [USC] or
USB and ISO SC [USIC]

FIG. 18

DOTDOT 225357 127




FIG. 19

OUT OF VDD




Fig. 21





Fig. 24








Fig. 20



Fl6.27



F16.28

DECLARATION AND POWER OF ATTORNEY FOR PATENT APPLICATION

Attorney Docket No.: 00AD11952023

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled: MULTI-MODE SMART CARD, SYSTEM AND ASSOCIATED METHODS, the specification of which:

(check one)

X is attached hereto

_____ was filed on _____

as Application Serial No. _____

and was amended on _____ (if applicable)

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulation, 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, 119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the of the application on which priority is claimed:

Prior Foreign Application(s) Priority Claimed

<u>(Number)</u>	<u>(Country)</u>	<u>(Day/Month/Year Filed)</u>	[<u> </u>]	[<u> </u>]
			Yes	No
<u>(Number)</u>	<u>(Country)</u>	<u>(Day/Month/Year Filed)</u>	[<u> </u>]	[<u> </u>]
			Yes	No
<u>(Number)</u>	<u>(Country)</u>	<u>(Day/Month/Year Filed)</u>	[<u> </u>]	[<u> </u>]
			Yes	No

I hereby claim the benefit under Title 35, United States Code, 120, of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, 1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

<u>(Appln Serial No.)</u>	<u>(Filing Date)</u>	<u>(Status)</u>
(patented, pending, aban.)		
<u>(Appln Serial No.)</u>	<u>(Filing Date)</u>	<u>(Status)</u>
(patented, pending, aban.)		

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

English Language Declaration

POWER OF ATTORNEY: As a named inventor, I hereby appoint the following attorneys to prosecute this application and transact all business in the Patent and Trademark Office connected therewith: Lisa K. Jorgensen, Reg. No. 34,845; Robert D. McCutcheon, Reg. No. 38,717; and Theodore E. Galantay, Reg. No. 24,122, all of STMicroelectronics, Inc., 1310 Electronics Drive, Carrollton, TX 75006; and Christopher F. Regan, Reg. No. 34,906; Herbert L. Allen, Reg. No. 25,322; Jeffrey S. Whittle, Reg. No. 36,382; David L. Sigalow, Reg. No. 36,006; Richard K. Warthar, Reg. No. 32,180; Michael W. Taylor, Reg. No. 43,182; Paul J. Dittmer, Reg. No. 40,455; Henry Estevez, Reg. No. 37,823; John F. Woodson, II, Reg. No. 45,236; Charles E. Wands, Reg. No. 25,649; Carl M. Napolitano, Reg. No. 37,405; Jacqueline E. Harte, Reg. No. 37,845; and Mark R. Malak, Reg. No. F-46,894, all of Allen, Dyer, Doppelt, Milbrath & Gilchrist, P.A., P.O. Box 3791, Orlando, FL 32802-3791.

Send Correspondence to:

Robert D. McCutcheon, Reg. No. 38,717
STMicroelectronics, Inc.
1310 Electronics Dr.
Carrollton, TX 75006

Direct Telephone Calls to:

ROBERT D. MCCUTCHEON
(972) 466-7511

Full name of first inventor: **Serge F. FRUANT**

Inventor's
Signature: Serge Fruant Date: 9/27/2000

Residence: **Saratoga, CA**
Citizenship: **Citizen of France**
Post Office Address: **18941 Cyril Place**
Saratoga, CA 95070

Residence: La Londe Les Maures, France
Citizenship: Citizen of France
Post Office Address: La Bastide, quartier RICHARD
53250 La Londe Les Maures, France

4